



### FEATURES

- 14 x 3 Watt LEDs
- 10° Lens Kit
- RGB Tri Color Pro Grade Economical Compact LED Par Can
- Uses 3-in-1 TRI LED System for Superior Color Mixing
- No Multi-Color Shadows
- Strobe effect
- Flicker free
- cETLus Approved

### TECHNICAL SPECIFICATIONS

- **DMX Channels:** 7 DMX Channels / 6 DMX work modes / Auto / Manual / Audio (TRI)
- **Control:** USITT DMX-512 (16-bit resolution), 3-pin and 5-Pin XLR serial input/output
- **Dimmer:** Smooth electronic dimming: 0 - 100%
- **Power Supply:** Multi-Voltage 100V~240V, 50/60Hz
- **Power Consumption:** 50W
- **Lamp:** 14 x 3 Watt LEDs - 42W (14 Red, 14 Green, 14 Blue)
- **Dimensions:** (LxWxH): 9" x 11" x 10.75" / 228 x 281 x 272 mm
- **Weight:** 6 lbs. / 2.5 kg

### PHOTOMETRIC DATA

10° Beam	1M	2M	3M	4M	5M
<b>Red</b>	2542	647	313	173	112
<b>Green</b>	8446	2177	1003	556	351
<b>Blue</b>	750	206	95	53	37
<b>Total</b>	11740	3020	1365	772	504

- Measurement in LUX

### OPTIONAL ACCESSORIES - LSF Series Light Shaping Filters

Order Code	Description
LSF536	LSF30-24 - 30° 24" x 24" Sheet
LSF537	LSF20-22 - 20° 24" x 22" Sheet
LSF538	LSF601-24 - 60 x 1° 24" x 24" Sheet
LSF539	LSF10-24 - 10° 24" x 24" Sheet

The ELED Tri PAR 56 by Elation Professional is an RGB TRI color PRO Grade economical compact LED par can featuring RGB additive color mixing using the 3-in-1 TRI-COLOR LED system providing smooth color mixing and no multi-color color shadows. The ELED Tri Par 56's optical system features 14 x 3W - 42 total watts. This fixture has five operating modes: sound active mode, macro mode, auto mode, auto mode speed adjustment and RGB mode. This unit also features flicker free 0-100% electronic dimming as well as a 10° lens kit. The ELED Tri Par 56 is designed for indoor use only and is fully operational in any safe working position.

### DMX TRAITS

#### 1 Channel Mode:

Channel	Value	Function
1	0 - 255	Macros

#### 2 Channel Mode:

Channel	Value	Function
1	0 - 255	Macros
2	0 - 255	Dimmer 0% - 100%

#### 3 Channel Mode:

Channel	Value	Function
1	0 - 255	Red 0% - 100%
2	0 - 255	Green 0% - 100%
3	0 - 255	Blue 0% - 100%

#### 4 Channel Mode:

Channel	Value	Function
1	0 - 255	Red 0% - 100%
2	0 - 255	Green 0% - 100%
3	0 - 255	Blue 0% - 100%
4	0 - 255	Dimming 0% - 100%

#### 6 Channel Mode:

Channel	Value	Function
1	0 - 255	Red 0% - 100%
2	0 - 255	Green 0% - 100%
3	0 - 255	Blue 0% - 100%
4	0 - 15	Nothing
	16 - 255	Color Macro
5	0 - 15	Nothing
	16 - 255	Strobe
6	0 - 255	Dimming 0% - 100%

#### 7 Channel Mode:

Channel	Value	Function
1	0 - 255	Red 0% - 100%
2	0 - 255	Green 0% - 100%
3	0 - 255	Blue 0% - 100%
4	0 - 15	Nothing
	16 - 255	Color Macro
5	0 - 15	Nothing
	16 - 255	Strobing / speed control
6	0 - 127	<u>Mode</u>
	128 - 159	Nothing
	160 - 191	Auto mix color
	192 - 223	3 color change
	224 - 255	7 color change
7	0 - 255	Sound active
	0 - 255	Dimming 0% - 100%

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>